

## NX-122P / NX-122

### 12V 2A Plug-In AC/DC Power Adapter

Compact plug-in power for CCTV cameras and security surveillance — residential and commercial use



The Nexakey NX-122P / NX-122 is a compact plug-in AC/DC power adapter delivering stable 12V 2A (24W) output for CCTV cameras, IP cameras, and small business surveillance systems. Its plug-in design eliminates external enclosures, making it ideal for clean, space-saving installations in residential and commercial environments.

#### KEY FEATURES

- ✓ **Stable 12V 2A Output** — regulated DC delivery prevents flicker and device resets for continuous surveillance
- ✓ **Plug-In Design** — compact form factor eliminates external boxes — plugs directly into AC outlets
- ✓ **Wide Input Range** — 100–240V AC, 50/60Hz — compatible with global voltage standards
- ✓ **97% High Efficiency** — minimal heat generation and low standby power consumption for energy savings
- ✓ **Pre-Wired DC Output** — 1.45m DC cable with standard 5.5mm/2.1mm barrel connector — ready to connect
- ✓ **Single Channel Output** — dedicated power supply for one camera or device — ideal for point installations

#### APPLICATIONS

- CCTV & IP Surveillance Cameras
- Analog & HD Cameras
- Residential Security Systems
- Small Business Camera Installations
- Access Control Devices (secondary use)
- Indoor / Outdoor Security Equipment

#### TECHNICAL SPECIFICATIONS

Model	NX-122P / NX-122	Adapter Type	Plug-In Switching Power Adapter
Input Voltage	100–240V AC	Input Frequency	50 / 60 Hz
Input Current	0.23A @ 230V AC (Max)	Output Voltage	DC 12V
Output Current	2A	Output Power	24W (Max)
Efficiency	97%	DC Cable Length	1.45m + DC 5.5/2.1mm Female
AC Cable Length	1.15m + Mains Plug	Operating Humidity	20% – 90% (Non-Condensing)
Storage Temperature	-20°C ~ +60°C	Country of Origin	China
Certifications	CE, FCC, RoHS		

#### CERTIFICATIONS

CE

FCC

RoHS